

LUT-ALCR-FM

Emergency Power Control For Switched Loads


Project:

Model No.:

Comments:



MOUNTING



APPLICATION

In the past, emergency lights were kept on 24 hours a day to meet life safety codes. Now, you can use a UL 924 listed [Emergency Power Control, Model LUT-ALCR-FM](#), to convert normal light fixtures into approved emergency lights. The [LUT-ALCR-FM](#) saves energy and money while ensuring compliance with both life safety and energy codes.

During normal operation, the same switch, occupancy sensor, relay panel, or lighting control can switch normal and emergency fixtures on and off simultaneously.

During a utility power interruption, the [LUT-ALCR-FM](#) automatically bypasses the normal lighting controls, turning the emergency lights ON, regardless of switch position.

The [LUT-ALCR-FM](#) is fixture mounted.

FEATURES


- Isolated 0-10V relay contact ensures full brightness during utility power interruption, regardless of dimmer model.
- Unique, Patented Automatic Diagnostic
When the room switch is turned off, the [LUT-ALCR-FM](#) will run a 2.5 self-test routine, verifying that the emergency power source was available and that the [LUT-ALCR-FM](#), ballast, and lamp(s) are all functioning correctly. This feature eliminates the need for time-consuming and costly manual monthly testing and is approved for this purpose. This also allows the unit to be installed in remote or inaccessible locations, because the unit does not rely on access to its manual test switch.
- Fire Alarm, Remote Test Option
- Utility & Emergency Power Indicator LED's
- Slim, profile allows mounting in most ballast channels.

Gary Gilgur
EM Supply LLC




(973) 650-0853
Sales@EM-Supply.com
www.EM-Supply.com

SINGLE LINE DRAWING



WIRING DIAGRAM



SPECIFICATIONS

ELECTRICAL	MODEL NO.	LUT-ALCR-FM
	SENSING INPUT	120V - 277V
	LED LOAD RATING	1A (120-277V)
	BALLAST LOAD RATING	5A (120-277V)
	INCANDESCENT LOAD	360W (120V) / 600W (277V)
	WARRANTY	5 Year Replacement Warranty

MECHANICAL	MOUNTING	Fixture Mount, Panel Mount
	RATING	UL94-5VA, Damp Location Rated
	SHIPPING WEIGHT / COLOR	8 oz. / Black
	TEMPERATURE	32°F - 140°F (0°C - 60°C)
	BODY SIZE	125mmx25.4mmx30mm (L x H x W)

Note: The LUT-ALCR-FM is intended to control one light fixture, for multiple fixtures please use LUT-ALCR

ORDERING INFORMATION

ADDITIONAL RESOURCES

LUT-ALCR-FM

- Installation Sheet
 - FAQ Sheet
 - Alternative Wiring Sheet
 - Terms & Conditions/Warranty Information
 - Fire Alarm Tie-In/Override
- www.lvscontrols.com/assets/UL924FAI.pdf

Gary Gilgur
EM Supply LLC



(973) 650-0853
Sales@EM-Supply.com
www.EM-Supply.com